




Electro-magnetic Valve

Usage: Electro-magnetic valve(also called diaphragm valve) is the “switch” for compressed air in the dust clean blowing system of the pulse bag filter. Controlled by the output signals of the pulse jet control device, it makes dust clean to the filter bags cell by cell to keep the resistance of the baghouse within the set range and thus guarantee the processing functions and the dust-collecting efficiency of the baghouse




Model NO.	EMCF-25
Working-pressure	0.4 ~ 0.6MPa
Ambient Temperature	-10 ~ 55℃
Relative Humidity	< 85%
Working Medium	Clean Air
Voltage	AC220V/DC24V
Diaphragm Life	Over One Million Cycles
Orifice	φ 25
Connection Port	1"


Model NO.	EMCF-40	EMCF-50	EMCF-65	EMCF-76
Working-pressure	0.4 ~ 0.6MPa			
Ambient Temperature	-10 ~ 55℃			
Relative Humidity	< 85%			
Working Medium	Clean Air			
Voltage	AC220V/DC24V			
Diaphragm Life	Over One Million Cycles			
Orifice	φ 40	φ 50	φ 65	φ 76
Connection Port	1-1/2"	2"	2-1/2"	3"
A	170	200	225	254



EMCYF-50



EMCYF-62



EMCYF-76

Model NO.	EMCYF-50	EMCYF-62	EMCYF-76
Working-pressure	0.2 ~ 0.6MPa		
Ambient Temperature	-10 ~ 55℃		
Relative Humidity	< 85%		
Working Medium	Clean Air		
Voltage	AC220V/DC24V		
Diaphragm Life	Over One Million Cycles		
Orifice	φ 50	φ 62	φ 76
Connection Port	φ 65	φ 80	φ 99

Muffler



Code	Screw Thread	φ
	Size	mm
SU-6	1/8"	16
SU-8	1/4"	20
SU-10	3/8"	24
SU-15	1/2"	24

SU Type Plastic Muffler



Code	Screw Thread	S
	Size	mm
CR-6	1/8"	14
CR-8	1/4"	17
CR-10	3/8"	20
CR-15	1/2"	24
CR-20	3/4"	30
CR-25	1"	36

Stainless Steel Muffler



Code	Screw Thread	S
	Size	mm
-M5	M5	9
-6A	1/8"	13
-8A	1/4"	17
-10A	3/8"	22
-15A	1/2"	24
-20A	3/4"	30
-25A	1"	36
-32A	1 1/4"	46
-40A	1 1/2"	52
-50A	2"	64

A Type Series Muffler



Code	Screw Thread	S
	Size	mm
SET-7	1/8"	8
SET-9.5	1/4"	10
SET-12.5	3/8"	13
SET-15.5	1/2"	15
SET-22	3/4"	19
SET-28	1"	24

SET Type Series Muffler Steel Copper Plating Feet



Code	Screw Thread	S
	Size	mm
-M5	M5	7
-6V	1/8"	12
-8V	1/4"	15
-10V	3/8"	19
-15V	1/2"	22
-20V	3/4"	30
-25V	1"	36

V Type Series Muffler



Plastic Porous Filter



Code	Screw Thread	S
	Size	mm
SD-6	1/8"	12
SD-8	1/4"	15
SD-10	3/8"	19
SD-15	1/2"	22
SD-20	3/4"	27
SD-25	1"	34

SD Type Speed Control Muffler



Code	Screw Thread	S
	Size	mm
B-6	1/8"	12
B-8	1/4"	15
B-10	3/8"	19
B-15	1/2"	22
B-20	3/4"	27
B-25	1"	34

B Type Exhaust Muffling Throttle Valve



Code	Screw Thread	S
	Size	mm
C-6	1/8"	13
C-8	1/4"	14
C-10	3/8"	17
C-15	1/2"	22
C-20	3/4"	27
C-25	1"	34

Ctype Exhaust Muffling Throttle Valve